MODEL	06C	C	2	28	A	1	0	0
DIGIT	1, 2, &3	4	5	6 & 7	8	9	10	11

1ST,2ND,3RD Digits Signify 06C Hermetic Recip. Compressor

4TH DIGIT - MODEL VARIABLE	
C	STANDARD MODEL
Y	SERVICE MODEL
8	SPECIAL ORDER

DESIGN VARIATION	
100	COMPRESSOR
101	PACKAGING w/o VALVES
102	PACKAGING w/ VALVES
103	SERVICE COMPRESSOR

5TH DIGIT - MOTOR SIZE		
0	15 FT-LB	5 HP
1	20 FT-LB	6.5 HP
2	24 FT-LB	8 HP
3	27 FT-LB	9 HP
5	45 FT-LB	15 HP
6	60 FT-LB	20 HP
7	75 FT-LB	25 HP
8	90 FT-LB	30 HP

6TH & 7TH DIGITS CFM
16 CFM
18 CFM
24 CFM
28 CFM
37 CFM
50 CFM
65 CFM
75 CFM
99 CFM

8TH DIGITS	ELECTRICAL CHARACTERISTICS VOLTS-PHASE-HERTZ	START
A	415 - 3 - 50	XL/PW
B	415 - 3 - 50	XL
C	415 - 3 - 50	PW
D	208/230 - 3 - 60	XL
E	208/230/400/460 - 3 - 50/60	SEE NOTE
F	400/460 - 3 - 50/60	XL/PW
G	400/460 - 3 - 50/60	XL
H	400/460 - 3 - 50/60	PW
J	575 - 3 - 60	XL
K	230 - 3 - 60	PW
L	230 - 3 - 60	XL/PW
M	220 - 3 - 50	XL
N	220 - 3 - 50	PW
P	220/346/380 - 3 - 50/60	XL/PW

NOTE:
CAN BE USED208/230/400/460 - 3 - 50/60 XL
OR
208-230 - 3 - 50/60 PW